### Specifications

#### **POWER SUPPLY**

separated for power and for logic (optional and not isolated):

Model	Power Supply	Current for each motor			
SW4D2070	12 ÷ 48 Vdc	0.0 ÷ 7.0 ARMS (10 APEAK)			

#### **COMMUNICATION INTERFACE**

Profine

#### **ENCODER INTERFACE**

incremental encoder for each motor not isolated input 5V Differential (RS422) or 5V Single-Ended (TTL/CMOS)

#### **USB INTERFACE**

service USB interface for programming and real time debug

#### **OPTOISOLATED INPUTS**

8 digital inputs

#### **OPTOISOLATED OUTPUTS**

4 digital outputs

#### **EMULATED STEP RESOLUTION**

Stepless Control Technology (65536 positions per turn)

#### **SAFETY PROTECTIONS**

Over/UnderVoltage, OverCurrent, OverTemperature, Phase/Phase and Phase/Ground Short

#### TEMPERATURE

operating from 5°C to 40°C, storage -25°C to 55°C

#### HUMIDITY

5% ÷ 85%

#### **PROTECTION CLASS**

IP20

# OpenLoop Position Controller AMP. Motor Closed Loop Controller Controller AMP. Motor

Better control compared to both an open loop stepper solution and a servo-controlled brushless solution

Feedback of OROUF - POSITION - SPEED

### Profinet Fieldbus vectorial drivers for 2 stepper motors









# **SW4**Titanio drivers

- Profinet
- Outputs to drive two independent motors
- USB serial for real time programming and debugging
- Compliance with the most common PLC Masters on the market
- Integrated oscilloscope
- Vectorial control, for smooth and silent movements
- Closed loop of speed, torque and position
- Easily programmable with e3PLC Programming Environment

# ELETTRONICA the clever drive

**ELETTRONICA PER AUTOMAZIONE INDUSTRIALE** Via del Commercio, 2/4 - 9/11

Loc. S. Grato - Z.I.

26900 - LODI (LO) - Italy

Tel. +39 0371 412318 - Fax +39 0371 412367 email infoever@everelettronica.it www.everelettronica.it

#### \_Proffma

#### Configuration programmable - c0990

Profinet DP is used for data exchange between controllers or PLC and IO devices or drives.

Main Profinet DP characteristics implemented in our drives are:

- develop with the Enhanced Real-Time Ethernet Controller 200P (siemens V4.6 PN Stack inside)
- GSDML V2.35 file
- it features an IRT switch (Dual Ethernet)
- it can be controlled over Profinet as an IO device
- supports RT (Real Time) protocol for Profinet IO, for applications with up to 10 ms cycle time: module 64 bytes I, 64 Bytes O
- supports IRT (Isochronous Real Time) protocol for Profinet IO, for applications with less than 1 ms cycle time: module 64 bytes I IRT, 64 Bytes O IRT
- it uses 64bytes (Input) and 64bytes (Output) to transfer IO data between the IO-Controller (PLC) and the IO-Device (SW5A Profinet)
- 16 bytes (I/O) are fixed mapped
- 40 bytes (I/O) may be variably mapped to desired drives functions using e3PLC.
- 8 bytes (I/O) are used to R/W Drive objects according to CANOpen SDO service
- additionally, digital I/O (24Vdc) and analog Inputs are available as distributed I/O points over Profinet



Drive control through commands by Master Controller

Suitable for multi axes systems, built in powerfull Motion Module functionality assures perfect synchronization among axes and reduces Master Controller workload **PLC Master** Profinet

Ever co. proprietary PC Software Tools for easy and quick configuration or programming, real time debug and supervision of each system

Autonomous management of the firmware for the execution of the *homing*, of the target movement with relative or absolute quota and for the generation of the ramp profiles

Torque mode for operation with torque limitation

Speed control thanks to digital inputs, analogue inputs or fieldbus

**Electronic CAM** with advanced programming of internal profiles inside the drive

**Electric shaft** with encoder or analogue input with variable tracking ratio (Electric Gear)

Fast inputs and outputs for motor' start & stop and event synchronization for high speed response applications such as labeling, nick finder, flying saw etc.

Possibility to synchronize the movements in multi-axis systems, even without fieldbus

Enabling and on-the-fly changing of the motion control modes

# Mechanical Data 43,5 U 00 194 43.5

Models		Dir H	Weight (g.)		
	SW4D2070T4S2-00	194.0	112.0	32.0	490

## Ordering Information for SWA Profinct drives

Ordering c	ng code Power			System resources				Control mode		
Versions	Config.	Power supply	Logic Power Supply	Current	Digital inputs	Digital outputs	Interface	Encoder	Service interface	Modes
SW4 EtherCAT drives Models										
SW4A2070T4S2-00	c0990	12 ÷ 48 Vdc	12 ÷ 48 Vdc	0 ÷ 7.1 Arms (0÷10.0 Apeak) for each motor	8	4	Profinet	Incremental for each motor	USB service for configuration, programming and debug in real time	Profinet mode

	Configuration and Programming Kits						
П	Kit code	Description					
	JSBC_SERV0EE-1M	USB service eePLC programming with cable and CD-Rom.					